


■ Manual Motor Starters

Series Standard	Type	Thermal current setting range Operational current Ie [A]	Max. motor capacity and full-load current 3-phase [HP]				Group Installation				UL File No.
			AC200-208V	AC220-240V	AC440-480V	AC550-600V	Rated breaking capacity [kA]			Max. fuse /MCCB	
							AC240V	AC480V	AC600V	Rated current [A]	
BM3 Series 	BM3RSB	0.1-0.16	-	-	-	-	100	50	10	500	E163944 (UL508)
		0.16-0.25	-	-	-	-	100	50	10	500	
		0.25-0.4	-	-	-	-	100	50	10	500	
		0.4-0.63	-	-	-	-	100	50	10	500	
		0.63-1	-	-	1/2	1/2	100	50	10	500	
		1-1.6	1/4	1/3	3/4	3/4	100	50	10	500	
		1.6-2.5	1/2	1/2	1	1 1/2	100	50	10	500	
		2.5-4	3/4	3/4	2	3	100	50	10	500	
		4-6.3	1	1 1/2	3	5	100	50	10	500	
		6.3-10	2	3	5	7 1/2	100	22	10	500	
		9-13	3	3	7 1/2	10	100	22	10	500	
		11-16	3	5	10	10	100	22	10	500	
		14-20	5	5	10	15	50	22	10	500	
		19-25	7 1/2	7 1/2	15	20	50	22	10	500	
	24-32	10	10	20	30	50	22	10	500		
	BM3RHB	0.1-0.16	-	-	-	-	100	50	10	500	
		0.16-0.25	-	-	-	-	100	50	10	500	
		0.25-0.4	-	-	-	-	100	50	10	500	
		0.4-0.63	-	-	-	-	100	50	10	500	
		0.63-1	-	-	1/2	1/2	100	50	10	500	
		1-1.6	1/4	1/3	3/4	3/4	100	50	10	500	
		1.6-2.5	1/2	1/2	1	1 1/2	100	50	10	500	
		2.5-4	3/4	3/4	2	3	100	50	10	500	
		4-6.3	1	1 1/2	3	5	100	50	10	500	
		6.3-10	2	3	5	7 1/2	100	50	10	500	
		9-13	3	3	7 1/2	10	100	50	10	500	
		11-16	3	5	10	10	100	50	10	500	
		14-20	5	5	10	15	100	50	10	500	
		19-25	7 1/2	7 1/2	15	20	100	50	10	500	
	24-32	10	10	20	30	100	50	10	500		
	BM3VSB	BM3VHB	6.3-10	2	3	5	7 1/2	100	50 (22)	10	600
			9-13	3	3	7 1/2	10	100	50 (22)	10	600
			11-16	3	5	10	10	100	50 (22)	10	600
14-20			5	5	10	15	100	50 (22)	10	600	
19-25			7 1/2	7 1/2	15	20	100	50 (22)	10	600	
24-32			10	10	20	30	100	50 (22)	10	600	
28-40			10	10	30	30	100	50 (22)	10	600	
35-50			15	15	30	40	100	50 (22)	10	600	
45-63	20	20	40	60	100	50 (22)	10	600			

Note 1: The figures in parentheses () are for BM3VSB.